


### 1 Prepare fixtures


Arrange boxed fixtures on the floor in specified mounting locations; remove fixtures and hardware from boxes.

**NOTE:** Leave the cardboard spacers and protective film installed until complete.




Remove fixture from packaging and locate hardware. Leave spacers in place for install.

### 2 Attach grid clips




Attach grid clips to fixture using supplied screws.

### 3 Install in ceiling grid




Pull down to engage clips onto T-bar.

### 4 Secure fixture




Secure fixture with grid wire or suitable equivalent per local and national building codes.

### 5 Connect Ethernet Cable




Insert Ethernet cable into female connector or on the top of the luminaire. Each luminaire should have one cable from the POE switch.

### 6 Remove spacers



Remove spacers and / or protective film. Cardboard and plastic film are recyclable where facilities exist

### Drywall Ceiling ONLY



**For drywall or inaccessible ceilings only:**

Lift and shift lens frame, rotating about hinge pins and remove.

Secure fixture to mounting frame by screwing through the holes in side of housing.

**! ATTENTION: Install in accordance with national and local building and electrical codes.**